

PROJECT TYPE

SPECIFICATION

# ZT5 ZHAGA BOOK 18

# BLUETOOTH MESH CONTROLLER

### **MAIN FEATURES**

- Casambi Bluetooth Wireless mesh controller
- For use in the following EnergyLite product families:
  - BroadLite
  - GridLite

#### CONSTRUCTION

• IP65 polycarbonate housing with UV protection

## **RATINGS + CERTIFICATIONS**

- IP65 and IK09 rated
- Contain no lead or mercury

## PERFORMANCE + FUNCTIONALITY

- Input voltage: 12-24V
- Input current: ≥20mA
- 0-10V PWM dimming, task tuning (10-100%)
- Bluetooth operation frequency 2.4GHz-2.483GHz
- Bluetooth transmission power: Up to +7dBm.
- Bluetooth transmission range: ≥50m (Typical outdoor)


**√** RoHS


• Operational Range of -20°C to 70°C

### WARRANTY


• 5-year warranty









PIN	Description	Lead wire color
1		
2		
3		
4		











Organize/edit luminaries, groups, and settings

Double-click 'Group' to control luminaires individually

Turn on/off all luminaries with one touch

Discover nearby unbound luminaries

Double-click individual luminaires to open settings

Gallery allows you to photograph different spaces to distinguish and control the luminaries visually

Scenes help control multiple luminaries

Network and Help





8655 Corporate Drive

Frisco, TX 75033





